



LED 2-Pin PL Ballast Compatibility Chart

Ballast Brand*	Part Number	# Of Lamps	Start Method	Lamp Connection	1 Lamp		2 Lamps	
					120V	277V	120V	277V
Keystone	CC579TP	1	NA	NA	✓	NA	-	-
Philips-Advance	VH-1B13-TP-W	1	NA	NA	NA	✓	-	-
Philips-Advance	H-1B13-TP-W	1	NA	NA	✓	NA	-	-
Philips-Advance	VH-2Q26-TP-BLS	2	PHS	-	NA	✓	NA	✓
Philips-Advance	VLO-2S13-TP	2	-	-	NA	✓	NA	✓
Philips-Advance	VLO-13-TP	1	-	-	NA	✓	-	-
Philips-Advance	H-2B13-TP-BLS	2	-	Parallel	✓	NA	✓	NA
Philips-Advance	LC-13-TP	1	-	NA	✓	NA	-	-
Philips-Advance	LC-14-20-C-TP	1	-	NA	✓	NA	-	-
Robertson	S28CP	1	PHS	NA	✓	NA	-	-
Robertson	HP2627P	1	PHS	NA	NA	✓	-	-
Robertson	S18PSC	1	PHS	NA	✓	NA	-	-
Robertson	HP21327SP	2	PHS	Series	NA	✓	NA	✓
Robertson	HP7927P	1	PHS	NA	NA	✓	-	-
Robertson	HP22627P	2	PHS	-	NA	✓	NA	✓
Robertson	HP1827P	1	PHS	NA	NA	✓	-	-
Robertson	S1P	1	-	NA	✓	NA	-	-
Robertson	O1527P(3P10104)	2	-	-	NA	✓	NA	✓
Robertson	SP4827P(3P10076)	1	-	-	NA	✓	-	-
Robertson	HP226SP(3P10085)	2	PHS	Series	✓	NA	✓	NA
Robertson	HP213P(3P10073)	2	PHS	Series	✓	NA	✓	NA
Robertson	HP28P	1	PHS	NA	✓	NA	-	-
Robertson	HP18P	1	PHS	NA	✓	NA	-	-
Robertson	HP218SP	2	PHS	Series	✓	NA	✓	NA

Applies to the
following Satco products:

S21411

F Flicker after >2s start-up (NC)
N Acoustic noise >20dB
P PF <0.85
T THD > 30%
NA Not applicable
HT High temperature

This list is current as of Feb. 2025. We are continuously testing for compatible ballasts. Please check back for updates.

* All trademarks are the property of their respective owners

110 Heartland Blvd.
Brentwood, NY 11717
PH 631-243-2022
FX 631-243-2027

Distribution Centers
New York, Florida,
Texas, Washington,
California, Puerto Rico

National Toll-Free
800-43-SATCO
(800-437-2826)
www.satco.com

Copyright© 2025
Satco Products, Inc.
All Rights Reserved.
Rev: February 25, 2025